


# Reset Box

## User Guide

# Introduction

The LA GARD 700 Series Reset Box is compatible with LA GARD Series Models 701-705 as well as 700 BASIC. The Reset Box is not compatible with Legacy LA GARD products that do not have a BAT Port (LA GARD BASIC, LA GARD Combogard Pro, LA GARD Auditgard).

## Connect the Reset Box

 Once the Reset Box is connected to a safe lock, deleted users cannot be recovered. All settings will be restored to the default values. While the Reset Box is connected to the lock, ALL communication from the Keypad is rejected. Access to the secured area MUST be maintained (keep the access door open) until the Reset Box is disconnected from the lock. If the access door is closed, the lock will have to be drilled to re-open.

Model	Reset Lock 700 Series Models 731-734	Reset 700 Series Models 7B1-7B3
<b>Reset Details</b>	<ul style="list-style-type: none"> <li>All Users except for Master will be deleted</li> <li>Master User Combination will be reset to default value 12345678</li> <li>All Settings will be restored to default values</li> </ul>	<ul style="list-style-type: none"> <li>Super Master Reset Code will return to default 55555555</li> <li>Manager Combination will return to default 123456</li> <li>User will be deleted</li> </ul>
<b>Reset Steps</b>	<ol style="list-style-type: none"> <li>Disconnect the safe lock from all power sources. The safe lock should also be disconnected from any Keypad or Multiplexer prior to connecting the Reset Box.</li> <li>Insert batteries into the Reset Box.</li> <li>Connect the Reset Box to the Safe Lock BAT port.</li> <li>The LED will illuminate and then stop when the reset is complete. DO NOT unplug the box before the reset is complete.</li> <li>Disconnect the Reset Box from the Safe Lock.</li> <li>Once successfully reset, the Master User Combination will be reset to 12345678.</li> <li>Reconnect the Safe Lock to the system.</li> </ol> <p><b>Note:</b> If the Reset Box LED does not turn on, disconnect the Reset Box, and repeat steps 1 and 2.</p>	<ol style="list-style-type: none"> <li>Remove batteries or disconnect the lock from any power source.</li> <li>Press and hold the 0 key for 10 seconds to discharge any residual energy.</li> <li>Connect the Reset Box to the Safe Lock BAT port.</li> <li>The Reset Box LED will illuminate for approximately 3 seconds, then stop when the reset is complete.</li> <li>Disconnect the Reset Box from the Safe Lock.</li> <li>Once successfully reset, the Manager Combination will be reset to the default 123456 and the Super Master Reset Code will return to default 55555555.</li> <li>Reconnect power to the lock. Test by opening the lock with the default Manager Combination of 123456.</li> </ol> <p><b>Note:</b> If the Reset Box LED does not turn on, disconnect the Reset Box, and repeat steps 1 and 2.</p>

# Specifications

## Battery

2 x 9V DC alkaline batteries (Eveready™ or Duracell™ strongly preferred)

## Cables

1 x 43109-3 cable

## Environmental

Operating & Storage Temperature Range: 32 – 122 °F (0 – 50 °C)

Relative Humidity Range: 0 – 95% non-condensing